



### Applications

- Designed to install at any chamber (incubator, oven, chiller, refrigerator, freezer, etc) with built-in Remote Alarm Terminal
- To transmit alarm or alert from the chamber via SMS to the user's mobile phone in the case of alarm occurrences

### Features

- Applicable to most type of temperature chamber with Built-in Remote Alarm Terminal
- Applies 2.4-inch TFT color screen and touch keyboard with built-in powerful CPU master
- Programmable up to six (6) SMS contacts
- Back-up memory system protects the preset contacts during power failure
- Integrated with backup battery to operate continuously up to 48hours in the case of power failure

### Specification

Model	QRGSM
Programmable SMS contact	6
Input Voltage	DC 5V / 1A
Standby Current	<55mA
Alarming Current	<450mA
Standby	Around 24 hours, Full charging time: 8hours
Built-in backup battery	NI-MH AAA*6 7.2V. (Rechargeable)
Excluded	Sim-Card
Optional	Temperature Alarm Monitoring System (QTM)

### Optional

For chamber does not come with built-in Remote Alarm Terminal, user may integrate with QRLAB's Temperature Alarm Monitoring System (QTM)

quantummaker